

**R15**

Code No: 124CU

JAWAHARLAL NEHRU TECHNOLOGICAL UNIVERSITY HYDERABAD

B.Tech II Year II Semester Examinations, December - 2017

ELECTROMAGNETIC THEORY AND TRANSMISSION LINES

(Common to ECE, ETM)

Time: 3 Hours

Max. Marks: 75

**Note:** This question paper contains two parts A and B.

Part A is compulsory which carries 25 marks. Answer all questions in Part A.

Part B consists of 5 Units. Answer any one full question from each unit.

Each question carries 10 marks and may have a, b, c as sub questions.

**PART-A****(25 Marks)**

- 1.a) Find Electric field intensity due to the charge distribution  $\rho_v$ . [2]
- b) Write poisson's and Laplace equations. [3]
- c) State Biot-Savart's law. [2]
- d) Calculate the self inductance per unit length of an infinitely long solenoid. [3]
- e) Write a wave equation in a lossy, charge free medium based on Maxwell's Equation. [2]
- f) What is Brewster angle? Write its equation. [3]
- g) What is condition for distortion less transmission line? [2]
- h) Explain how Quarter wave transformer is used for matching? [3]
- i) What is the value of characteristic impedance and reflection coefficient for an open circuited line? [2]
- j) What are the characteristics of smith chart? [3]

**PART-B****(50 Marks)**

- 2.a) Point charges 5nC and -2nC are located at (2,0,4) and (3,0,5), respectively. Find the electric field at (1,-3,7).
- b) Given that  $E=(3x^2+y_0a_x+xa_y)$  kV/m, find the work done in moving a  $-2\mu\text{C}$  charge from (0,5,0) to (2,-1,0) by taking the path. [5+5]

**OR**

- 3.a) An electric dipole of  $100a_z\text{pC}\cdot\text{m}$  is located at the origin. Find  $V$  and  $E$  at point  $(1,\pi/3,\pi/2)$ .
- b) Three point charges -1nC, 4nC, and 3nC are located at (0,0,0),(0,0,1) and (1,0,0) respectively. Find the energy in the system. [5+5]

- 4.a) A circular loop located on  $x^2+y^2=9, z=0$  carries a direct current of 10A along  $a_\phi$ . Determine  $H$  at (0,0,4) and (0,0,-4).
- b) In a certain conducting region,  $H=yz(x^2+y^2)a_x-y^2xza_y+4x^2y^2a_z\text{mA/m}$ . Determine  $J$  at (5,2,-3). [5+5]

**OR**

- 5.a) State Maxwell's equations in an integral and word form.
- b) A unit normal vector from region 2 ( $\mu=2\mu_0$ ) to region 1 ( $\mu=\mu_0$ ) is  $a_{n21}=(6a_x+2a_y-3a_z)/7$ . If  $H_1=10a_x+a_y+12a_z$  A/m and  $H_2=H_{2x}a_x-5a_y+4a_z$  A/m. Determine  $H_{2x}$ . [5+5]

6.a) A lossy material has  $\mu=5\mu_0$ ,  $\epsilon=\epsilon_0$ . If at 5 MHz, the phase constant is 10 rad/m, calculate the loss tangent, conductivity of the material, complex permittivity attenuation constant and intrinsic impedance.

b) Derive the equation for intrinsic impedance in lossless dielectrics. [5+5]

OR

7.a) Determine the Fresnel coefficients for oblique incidence from lossless medium 1 to lossless medium 2 for parallel polarization.

b) Region 1 is a lossless medium for which  $y \geq 0$ ,  $\mu=\mu_0$ ,  $\epsilon=4\epsilon_0$ , whereas region 2 is free space,  $y \leq 0$ . If a plane wave  $E=5\cos(108t+\beta t)a_z$  V/m exists in region 1, find the time average pointing vector. [5+5]

8.a) A transmission line operating at 500MHz has  $Z_0=80\Omega$ , Propagation constant =  $0.04$  Np/m;  $\beta=1.5$  rad/m. Find the line parameters R, L, G and C?

b) Find the  $Z_{in}$  at any point on the line in terms load impedance starting from voltage and current wave equations on line. [5+5]

OR

9.a) For a lossless two wire transmission line show that the Characteristic impedance  $Z_0 = \frac{120}{\sqrt{\epsilon_r}} \cosh^{-1} \frac{d}{2a}$ .

b) A lossless transmission line operating at 4.5GHz has  $L=2.4\mu\text{H}/\text{m}$  and  $Z_0=85\Omega$ . Calculate the phase constant and the phase velocity. [5+5]

10.a) A  $500\Omega$  lossless line has  $V_L = 10e^{j25^\circ}$  V and  $Z_L = 50e^{j30^\circ}\Omega$ . Find the current at  $\lambda/4$  from the load?

b) A  $60\Omega$  air line operating at 20MHz is 10m long. If the input impedance is  $90 + j150\Omega$ . Calculate  $Z_L$ ,  $\Gamma$  and S. [5+5]

OR

11. Explain how double stub is used for matching with suitable diagram? Derive equations for its length and location. [10]

---ooOoo---